Furutech ADL A1 ASIO Driver installation guide for Windows

To install the driver for Furutech ADL A1:

- 1. Download the driver from the A1 webpage: http://www.adl-av.com/products/headphone_amplifiers/A1/
- 2. Double-click the .zip file to open and save to hard drive
- 3. Connect Furutech ADL A1 to PC with provided USB cable and switch the A1 on. (No driver should be found for Furutech ADL A1)
- 4. Switch on the rear side of the A1 should be set to "USB Dac".
- 5. Open Furutech ADL A1 ASIO Driver folder and double click on SETUP.EXE to install Furutech ADL A1 driver on the PC.

Song and Forgeth ADL AT ASID Driver							
组合管理 • 🔂 開設	共用對象 · 原蜂	新油資料交				Description for the stall	
☆ 我的希美	84	修改且期	和型 :	大小		Preparing to Install	
TR	DIFXAPI	2014/2/18 上午 0	模型实际实				
HAN .	🗼 viaudusb	2014/2/18 上午 0	福富资料实			Platform Setup is preparing the instalishield wizard, which	
9月 最近的位置	0X0409.INE	2002/5/2 下牛 03	组制股工	5 KB		will guide you through the program setup process. Pleas	
MySyncFolder	A 165x300.bmp	2009/7/19 上年 0	私知思影像	146 KB		wait.	
	500x60.bmp	2009/7/6 上午 10	贴端医影像	90 KB			
- 保持項	asia.slf	2007/9/19 上午 0	SLF 幅震	36 KB			
D to	english.dll	2011/3/14 下午 0	唐用程式描充	431 KB			
日日日本] english.slf	2007/9/19 上年 0	SLF 個面	7 KS		Checking Uperating System Version	
h min	europe1.slf	2007/9/19 上午 0	SLF 煤雪	60 KB			
● 視氏 ■ 視氏 ■ 圏片	europe2.slf	2007/9/19 上年 0	SLF模式	49 KB			
	europe3.slf	2007/9/19 上午 0	SLF 僅富	50 KB			
	europe4.slf	2007/9/19 上年 0	SLF 檔案	27 KB			
🜏 家用数组	SINSTMSIA.EXE	2002/3/11 上午 0	用用程式	1,669 KB			
	INSTMSIW.EXE	2002/3/11 上午 1	應用程式	1,780 KB			
80.0	ISSCRIPT.MSI	13 下午 0	Windows Installe	617 K8			
1 TE	LICENSE.MLF	19 上午 0	MLF 編宽	3 KB			
🏭 本機磁碼 (C:)	Platform msi	0 ± 41	Windows Installe	2,681 KB			
5% 本機磁環 (D:)	SETUP.EXE	0上午1	康用模式	212 KB			
MSN 上我的社群	@ Setup.ini	10上午1	组展設定	2 KB			
1 .1838	Setupliss	19上午0	ISS 档案	1 KS			
	SETUP.MLF	2001/1/19上中 0	MLF 编部	228 KB			
	SETUP	2013/12/24 下中	Windows Explor	1 KB	The second se		
🚯 image Catalog	VIAPCI.sys	2011/3/14 下午 0	系统描言	10 KB			
	🗟 viasetup.dll	2011/3/14 下午 0	度用程式提充	119 KB			
	viaudio.ini	2013/12/24 下年	用限股票	1 KB		Can	

- 6. Continue through the installation process by clicking "Next" until the final step to automatically restart PC. Select "Restart Computer" and click on "Finish".
- 7. Once PC has restarted, the ADL A1 Driver will be successfully installed.
- Please check if the ADL A1 ASIO icon is on the desktop screen to confirm successful installation.
 Click on the ADL A1 ASIO icon and adjust the ASIO Buffer Size to maximum to ensure smooth playback.

M	🖁 VIA DirectKS ASIO Full Duplex Setup						
TC	DirectKS Output Ports		ASIO Buffer Size				
ADL A1 ASIO	Device Name	Active	Current Size: 4096 Samples				
		103	Change the size to: 4096 Samples				
	DirectKS Input Ports						
	Device Name	Active					
			Apply Cancel				

Furutech A1 Driver Uninstall Guide

WARNING: Please make sure Furutech A1 is connected to computer and A1 unit is switched on before uninstalling.

Uninstalling without Furutech A1 connecting to computer will result in failure to uninstall.

Step 1: Connect A1 to the PC and proceed to the Control Panel > Programs and Features and select VIA control manager (shown below) and click uninstall.

